

OMRON 变频器3G3JV (0.4~160kW) 适配的三相进线电抗器和直流电抗器三相输出电抗器

电源电压 V	电机功率 kW	变频器型号 3G3RV	输出电流 A	三相进线电抗器			直流电抗器					三相输出电抗器		
				相电流 A	OMRON 订货号 3G3IV-PUZB	德润 订货号 DZ-3HG-	结构号	相电流 A	OMRON 订货号 3G3HV-PUZD	德润 订货号 DZ-3ZG-	结构号 结构号	电流 A	OMRON 订货号	德润 订货号 DZ-3CG-
3AC 200 ~240	0.4	-A2004	3.2	2.5	AB2.5A4.2MH	OM02	1	5.4	AB5.4A8MH	OM01	2	4	OM02	1
	0.75	-A2007	4.1	5	AB5A2.1MH	OM03	1							
	1.5	-A2015	7	10	AB10A1.1MH	OM04	1	18	AB18A3MH	OM02	7	10	OM04	3
	2.2	-A2022	9.6	15	AB15A0.71MH	OM05	2							
	3.7	-A2037	15	20	AB20A0.53MH	OM06	3	36	AB36A1MH	OM03	8	25	OM07	5
	5.5	-A2055	23	30	AB30A0.35MH	OM07	4							
	7.5	-A2075	31	40	AB40A0.265MH	OM08	5	72	AB72A0.5MH	OM04	11	50	OM08	7
	11	-A2110	45	60	AB60A0.18MH	OM09	6							
	15	-A2150	58	80	AB80A0.13MH	OM10	7	9	AB90A0.4MH	OM05	11	75	OM09	9
	18.5	-A2185	71	90	AB90A0.12MH	OM11	7							
	22	-B2220	85	120	AB120A0.09MH	OM12	8	120					OM10	9
	30	-B2300	115	160	AB160A0.07MH	OM13	9							
	37	-B2370	145	200	AB200A0.05MH	OM14	10	150					OM11	11
	45	-B2450	180	240	AB240A0.044MH	OM15	10							
	55	-B2550	215	280	AB280A0.038MH	OM16	11	180					OM12	11
	75	-B2750	283	370		OM17	12							
90	-B2900	346	450		OM18	12	220					OM13	11	
110	-B211K	415	540		OM19	13								
3AC 380 ~460	0.4	-A4004	1.8	1.3	AB1.3A18MH	OM21	1	3.2	AB3.2A28MH	OM21	3	3	OM21	1
	0.75	-A4007	2.1	2.5	AB2.5A8.4MH	OM22	1							
	1.5	-A4015	3.7	5	AB5A4.2MH	OM23	1	5.7	AB5.7A11MH	OM22	4	6	OM23	3
	2.2	-A4022	5.3	7.5	AB7.5A3.6MH	OM24	3							
	3.7	-A4037	7.6	10	AB10A2.2MH	OM25	3	12	AB12A6.3MH	OM23	7	14	OM24	5
	5.5	-A4055	12.5	15	AB15A1.42MH	OM26	4							
	7.5	-A4075	17	20	AB20A1.06MH	OM27	5	23	AB23A3.6MH	OM24	9	24	OM25	7
	11	-A4110	24	30	AB30A0.7MH	OM28	6							
	15	-A4150	31	40	AB40A0.53MH	OM29	7	33	AB33A1.9MH	OM25	9	40	OM26	9
	18.5	-A4185	39	50	AB50A0.42MH	OM30	7							
	22	-B4220	45	60	AB60A0.36MH	OM31	8	47	AB47A1.3MH	OM26	11	50	OM27	9
	30	-B4300	60	80	AB80A0.26MH	OM32	9							
	37	-B4370	75	90	AB90A0.24MH	OM33	10	60					OM28	10
	45	-B4450	91	120	AB120A0.18MH	OM34	10							
	55	-B4550	112	150	AB150A0.15MH	OM35	11	80					OM29	10
	75	-B4750	150	200		OM36	12							
90	-B4900	180	240		OM37	12	91					OM30	11	
110	-B411K	216	280		OM38	13								
132	-B413K	260	340		OM39	13	112					OM31	11	
160	-B416K	304	400		OM40	13								
												150	OM32	12
												180	OM33	12
												220	OM34	13
												260	OM35	13
												310	OM36	13

OMRON 变频器3G3JV (0.1~3.7kW) 适配的三相进线电抗器和直流电抗器

电源电压 V	电机功率 kW	变频器型号 3G3JV	输出电流 A	三相进线电抗器			直流电抗器			三相输出电抗器				
				相电流 A	OMRON 订货号	德润 订货号	结构号	电流 A	OMRON 订货号	德润 订货号	结构号	电流 A	OMRON 订货号	德润 订货号
3AC 200 ~240	0.1	-A2001	0.8	2	3G3JV-PUZB	DZ-3HG		5.4	3G3HV-PUZD	DZ-3ZG		3	DZ-3CG	
	0.2	-A2002	1.6	2	AB2A7MH	OM01	1	AB5.4A8MH			2	3	OM01	1
	0.4	-A2004	3	2.5	AB2.5A4.2MH	OM02	1							
	0.75	-A2007	6	5	AB5A2.1MH	OM03	1					6	OM03	1
	1.5	-A2015	8	10	AB10A1.1MH	OM04	1							
	2.2	-A2022	11	15	Ab15a0.71MH	OM05	2	18	AB18A3MH	OM02	7	12	OM05	3
3AC 380 ~460	3.7	-A2037	17.5	20	AB20A0.53MH	OM16	3					18	OM06	4
	0.2	-A4002	1.2	1.3	AB1.3A18MH	OM21	1							
	0.4	-A4004	1.8	2.5	AB2.5A8.4MH	OM22	1	3.2	AB3.2A2.8MH	OM21	3	4	OM22	3
	0.75	-A4007	3.4	5	AB5A4.2MH	OM23	1							
	1.5	-A4015	4.8	5	AB5A4.2MH	OM23	1							
	2.2	-A4022	5.5	7.5	AB7.5A3.6MH	OM24	3	5.7	AB5.7A11MH	OM22	4	6	OM23	3
3.7	-A4037	8.6	10	AB10A2.2MH	OM25	3	12	AB12A6.3MH	OM23	7	14	OM24	5	