

ABB 直流调速器 DCS401、402 (9-520kW)适配的三相进线电抗器

三相进线电抗器									
电机功率 Kw	ABB 直流调速器	直流 电压 V	直流 电流 A	交流 电流 A	相电流 A	ABB 型号	德润 订货号 DZ-3HG	结构号	
400V	500V	型号	象限						
9	12	DCS401-0020	2Q	20	16				
10	13	DCS402-0025	4Q	25	20	18.5	ND401	-B401	4
		DCS401-0045	2Q	45	36				
21	26	DCS402-0050	4Q	50	41	37	ND402	-B402	6
		DCS401-0065	2Q	65	52				
31	39	DCS402-0075	4Q	75	61	55	ND403	-B403	7
		DCS401-0090	2Q	90	74				
41	52	DCS402-0100	4Q	100	82	74	ND404	-B404	9
		DCS401-0125	2Q	125	102				
58	73	DCS402-0140	4Q	140	114	104	ND405	-B405	9
		DCS401-0180	2Q	180	147				
83	104	DCS402-0200	4Q	200	163	148	ND406	-B406	10
		DCS401-0230	2Q	230	188				
107	133	DCS402-0260	4Q	260	212	192	ND407	-B407	11
		DCS401-0315	2Q	315	257				
146	183	DCS402-0350	4Q	350	286	252	ND408	-B408	12
		DCS401-0405	2Q	405	330				
187	234	DCS402-0450	4Q	450	367	332	ND409	-B409	12
		DCS401-0500	2Q	500	408				
232	290	DCS402-0550	4Q	550	448	406	ND410	-B410	13
		DCS401-0610	2Q	610	498				
284	354	DCS402-0680	4Q	680	555	502	ND411	-B411	13
		DCS401-0740	2Q	740	604				
344	429	DCS402-0820	4Q	820	669	605	ND412	-B412	14
		DCS401-0900	2Q	900	735				
419	522	DCS402-1000	4Q	1000	816	740	ND413	-B413	14

ABB 直流调速器、变频器适配的三项进项电抗器技术数据

订货号	额定 电流	电感 Ln	I _{Ln} 50Hz 电压降 ΔU U	额定 电压 Un V	重量约 kg	结构号 No	订货号	额定 电流	电感 Ln	I _{Ln} 50Hz 电压降 ΔU U	额定 电压 Un V	重量约 kg	结构号 No
DZ-	I _{Ln} A	μH	ΔU U	Un V	kg	No	DZ-	I _{Ln} A	μH	ΔU U	Un V	kg	No
直流调速器用							变频器用						
3ZG-B01	18	512	2.9		1.0	3	3HG-B20	8.5	3500	9.34		2.0	5
3ZG-B02	37	250	2.9		2.0	5	3HG-B21	11.5	2800	10.1		3.0	5
3ZG-B03	37	300	3.5		3.0	5	3HG-B22	16	2000	10		6.0	6
3ZG-B04	55	168	2.9		3.0	6	3HG-B23	18.5	1550	9		6.0	6
3ZG-B05	82	135	3.5		6.0	7	3HG-B24	27	1200	10.1		7.5	7
3ZG-B06	102	90	2.9		6.0	7	3HG-B25	34	630	6.7		6.0	7
3ZG-B07	184	50	2.9		10	9	3HG-B26	42	400	5.28		6.0	7
3ZG-B08	196	56.3	3.5		11.5	9	3HG-B27	50	440	6.91		7.5	8
3ZG-B09	245	37.5	2.9		11.5	9	3HG-B28	68	330	7		10	9
3ZG-B10	367	25	2.9		22	11	3HG-B29	84	250	6.6		11.5	9
3ZG-B11	326	33.8	3.5		22	11	3HG-B30	118	220	8.16		26	11
3ZG-B12	490	18.8	2.9		26	12	3HG-B31	168	180	9.5		40	12
3ZG-B13	698	18.2	4	400	40	13	3HG-B32	200	135	8.48		40	12
3ZG-B14	930	9.9	2.9	~	40	13	3HG-B33	240	110	8.3	400	50	13
3ZG-B15	1163	10.9	4	690	50	14	3HG-B34	290	90	8.2	~	50	13
3ZG-B16	1510	6.1	2.9		50	14	3HG-B35	355	75	8.36	500	50	14
							3HG-B36	490	60	8.3		80	14
							3HG-B37	540	48	8.14		80	14
							3HG-B38	18	3900	22		7.5	9
							3HG-B39	22	2600	18		7.5	9
							3HG-B40	33	1300	13.5		10	9
							3HG-B41	55	1000	17.3		22	11
							3HG-B42	77	670	16.2		40	12
							3HG-B43	132	400	16.6		50	13
							3HG-B44	187	270	15.9		80	14
							3HG-B45	286	190	17		110	15
							3HG-B46	440	130	18		140	17