

FUJI 变频器 FRNG/P (0.4~110 kW) 适配的三相进线电抗器、直流电抗器

额定 交流 电源 电压 V	电机 额定 功率 kW	富士变频器		三相进线电抗器			直流电抗器					
		型 号	输出 电压 V	输出 电流 A	相电流 A	FUJI 订货号	德润 订货号	结构号	直流 电流 A	FUJI 订货号	德润 订货号	结构号
	0.2	FVR002G7S-2EX							1.5	DCR2-0.2	DZ-3ZG-F01	1
	0.4	FVR004G7S-2EX			3	ACR2-0.4A	DZ-3HG-F01	1	3	DCR2-0.4	DZ-3ZG-F02	1
	0.75	FVR008G7S-2EX			5	ACR2-0.75A	DZ-3HG-F02	1	5	DCR2-0.75	DZ-3ZG-F03	1
	1.5	FVR015G7S-2EX			8	ACR2-1.5A	DZ-3HG-F03	1	8	DCR2-1.5	DZ-3ZG-F04	2
	2.2	FVR022G7S-2EX			11	ACR2-2.2A	DZ-3HG-F04	1	11	DCR2-2.2	DZ-3ZG-F05	4
	4	FVR040G7S-2EX			17	ACR2-3.7A	DZ-3HG-F05	1	18	DCR2-3.7	DZ-3ZG-F06	4
	5.5	FVR055G7S-2EX			25	ACR2-5.5A	DZ-3HG-F06	2	25	DCR2-5.5	DZ-3ZG-F07	6
	7.5	FVR075G7S-2EX			33	ACR2-7.5A	DZ-3HG-F07	3	34	DCR2-7.5	DZ-3ZG-F08	6
3AC	11	FVR110G7S-2EX	3AC		48	ACR2-11A	DZ-3HG-F08	4	50	DCR2-11	DZ-3ZG-F09	8
200	15	FVR150G7S-2EX	50Hz		59	ACR2-15A	DZ-3HG-F09	5	67	DCR2-15	DZ-3ZG-F10	9
+10%	18.5	FVR185G7S-2EX	200		74	ACR2-18.5A	DZ-3HG-F10	6	81	DCR2-18.5	DZ-3ZG-F11	10
-15%	22	FVR220G7S-2EX			87	ACR2-22A	DZ-3HG-F11	6	98	DCR2-22	DZ-3ZG-F12	11
	30	RFN30G9/P9S-2JE		115					150	DCR2-30	DZ-3ZG-F13	12
	37	RFN37G9/P9S-2JE		145	200	ACR2-37	DZ-3HG-F12	8	180	DCR2-37	DZ-3ZG-F14	13
	45	RFN45G9/P9S-2JE		180					220	DCR2-45	TCR425-F01	1
	55	RFN55G9/P9S-2JE		215	270	ACR2-55	DZ-3HG-F13	9	270	DCR2-55	TCR425-F02	1
	75	RFN75G9/P9S-2JE		283	390	ACR2-75	DZ-3HG-F14	10	370	DCR2-75	TCR425-F03	2
	90	RFN90G9/P9S-2JE		346	460	ACR2-90	DZ-3HG-F15	11	450	DCR2-90	TCR425-F04	2
	110	RFN110G9/P9S-2JE		415	500	ACR2-110	DZ-3HG-F16	11	550	DCR2-110	TCR425-F05	3

## FUJI 变频器 FRNG/P (0.4~280 kW) 适配的三相进线电抗器、直流电抗器和三相输出电抗器

额定 交流 电源 电压 V	电机 额定 功率 kW	富士变频器			三相进线电抗器			直流电抗器			三相输出电抗器					
		型 号	输出 电压 V	输出 电流 A	相电流 A	FUJI 订货号	德润 订货号	结 构 号	直流 电流 A	FUJI 订货号	德润 订货号	结 构 号	相电流 A	FUJI 订货号	德润 订货号	结构号
3AC 380~440 +10% -15%	0.4	FRN0.4G/P11S-4CX		1.5				1.5	DCR4-0.4A	DZ-3ZG-F15	1					
	0.75	FRN0.75G/P11S-4CX		2.5	2.5	ACR4-0.75A	DZ-3HG-F17	1	2.5	DCR4-0.75A	DZ-3ZG-F16	3	4		DZ-3CG-F01	1
	1.5	FRN1.5G/P11S-4CX		3.7	3.7	ACR4-1.5A	DZ-3HG-F18	1	4	DCR4-1.5A	DZ-3ZG-F17	3				
	2.2	FRN2.2G/P11S-4CX		5.5	5.5	ACR4-2.2A	DZ-3HG-F19	1	5.5	DCR4-2.2A	DZ-3ZG-F18	4	6		DZ-3CG-F02	3
	3.7	FRN3.7G/P11S-4CX		9	9	ACR4-3.7A	DZ-3HG-F20	1	9	DCR4-3.7A	DZ-3ZG-F19	5				
	5.5	FRN5.5G/P11S-4CX		13	13	ACR4-5.5A	DZ-3HG-F21	3	13	DCR4-5.5A	DZ-3ZG-F20	6	13		DZ-3CG-F03	5
	7.5	FRN7.5G/P11S-4CX		18	18	ACR4-7.5A	DZ-3HG-F22	4	18	DCR4-7.5A	DZ-3ZG-F21	7	18		DZ-3CG-F04	5
	11	FRN11G/P11S-4CX		24	24	ACR4-11A	DZ-3HG-F23	4	25	DCR4-11A	DZ-3ZG-F22	8	24		DZ-3CG-F05	7
	15	FRN15G/P11S-4CX		30	30	ACR4-15A	DZ-3HG-F24	5	34	DCR4-15A	DZ-3ZG-F23	9	30		DZ-3CG-F06	7
	18.5	FRN18.5G/P11S-4CX	3AC 50Hz	39	39	ACR4-18.5A	DZ-3HG-F25	6	41	DCR4-18.5A	DZ-3ZG-F24	10	40		DZ-3CG-F07	8
	22	FRN22G/P11S-4CX	380	45	45	ACR4-22A	DZ-3HG-F26	6	49	DCR4-22A	DZ-3ZG-F25	11	45		DZ-3CG-F08	9
	30	FRN30G/P11S-4CX		60					80	DCR4-30A	DZ-3ZG-F26	13	60	OR0-30-4A	DZ-3CG-F21	10
	37	FRN37G/P11S-4CX		75	100	ACR4-37A	DZ-3HG-F27	8	100	DCR4-37A	TCR425-F16	1	75	OR0-37-4A	DZ-3CG-F22	10
	45	FRN45G/P11S-4CX		91					120	DCR4-45A	TCR425-F06	1	91	OR0-45-4A	DZ-3CG-F23	10
	55	FRN55G/P11S-4CX	(440)	112	135	ACR4-55A	DZ-3HG-F28	9	146	DCR4-55A	TCR425-F07	2	112	OR0-55-4A	DZ-3CG-F24	11
	75	FRN75G/P11S-4CX		150	160	ACR4-75A	DZ-3HG-F29	10	150	DCR4-75A	TCR425-F08	1	150	OR0-75-4A	DZ-3CG-F25	12
	90	FRN90G/P11S-4CX		176					176	DCR4-90A	TCR425-F09	1	176	OR0-90-4A	DZ-3CG-F26	13
	110	FRN110G/P11S-4CX		210	250	ACR4-110A	DZ-3HG-F30	11	211	DCR4-110A	TCR425-F10	2	210	OR0-110-4A	DZ-3CG-F27	13
	132	FRN132G/P11S-4CX		253	270	ACR4-132A	DZ-3HG-F31	13	356	DCR4-132A	TCR425-F11	6	253	OR0-132-4A	DZ-3CG-F28	13
	160	FRN160G/P11S-4CX		304					395	DCR4-160A	TCR425-F12	6	304	OR0-160-4A	DZ-3CG-F29	14
200	FRN200G/P11S-4CX		377	581	ACR4-220A	DZ-3HG-F32	14	494	DCR4-200A	TCR425-F13	7	377	OR0-200-4A	DZ-3CG-F30	14	
220	FRN220G/P11S-4CX		415					557	DCR4-220A	TCR425-F14	7	415	OR0-220-4A	DZ-3CG-F31	15	
280	FRN280G/P11S-4CX		520	825	ACR4-280A	DZ-3HG-F33	15	700	DCR4-280A	TCR425-F15	8	520	OR0-280-4A	DZ-3CG-F32	15	